

# FUSIBILI CILINDRICI INDUSTRIALI PORTAFUSIBILI SEZIONABILI SERIE "BCH"

## INDUSTRIAL CYLINDRICAL FUSES SERIES "BCH" MODULAR FUSEHOLDERS

### Descrizione

Il corpo del portafusibile si presenta con un design moderno ed è realizzato in materiali termoplastici autoestinguenti e resistenti alle elevate temperature (tutti i materiali sono UL listed) mentre i relativi contatti sono in rame argentato. Tutti i portafusibili sezionabili sono piombabili per la sicurezza degli operatori durante le manutenzioni. I fusibili devono essere ordinati separatamente.

### Description

The fuseholder body has a very modern design and is made of self-extinguishing thermoplastic material which is resistant to high temperatures (all materials are UL listed). The fuseholder contacts are in silver plated copper. All modular fuseholders can be sealed during maintenance operations for operators' safety. Fuses have to be ordered separately.

### Norme - Standards

IEC EN 60269-1  
IEC EN 60269-2  
IEC EN 60947-3  
VDE 0636



Portafusibile sezionabile  
BCH 1x38

BCH 1x38 modular fuseholder



Portafusibile sezionabile  
BCH 1x51

BCH 1x51  
modular fuseholder



Portafusibile sezionabile  
BCH 1x58

BCH 1x58  
modular fuseholder

### BCH 38 - PORTAFUSIBILI SEZIONABILI (AC-22B) PER FUSIBILI CILINDRICI 10,3X38 BCH 38 - MODULAR FUSEHOLDERS (AC-22B) FOR 10,3X38 CYLINDRICAL FUSES

codice IW IW code	tipo type	n. poli poles	n. moduli 17,5 mm no. 17,5 mm modules	indicatore luminoso indicator light	micro microswitch	I <sub>n</sub> (A) I <sub>n</sub> (A)	V <sub>n</sub> (V) V <sub>n</sub> (V)	conf. pack.
2301038	BCH 1x38	1P	1	—	—	32A	690V	12-240
2304138	SBCH 1x38	1P	1	X	—	32A	690V	12-240
2301137	NBCH 1x38	1P+N	1	—	—	32A	690V	12-240
2301138	BCH 1x38N	1P+N	2	—	—	32A	690V	6-120
2302038	BCH 2x38	2P	2	—	—	32A	690V	6-120
2303038	BCH 3x38	3P	3	—	—	32A	690V	4-80
2304338	SBCH 3x38	3P	3	X	—	32A	690V	4-80
2303137	NBCH 3x38	3P+N	3	—	—	32A	690V	4-80
2303138	BCH 3x38N	3P+N	4	—	—	32A	690V	3-60

Omologazione esclusi i tipi NBCH 1x38 e NBCH 3x38  
(per questi tipi la categoria d'impiego è AC-20B)

approval except types NBCH 1x38 and NBCH 3x38  
(for these types the utilization category is AC-20B)

### BCH 51 - PORTAFUSIBILI SEZIONABILI (AC-22B) PER FUSIBILI CILINDRICI 14X51 BCH 51 - MODULAR FUSEHOLDERS (AC-22B) FOR 14X51 CYLINDRICAL FUSES

codice IW IW code	tipo type	n. poli poles	n. moduli 17,5 mm no. 17,5 mm modules	indicatore luminoso indicator light	micro microswitch	I <sub>n</sub> (A) I <sub>n</sub> (A)	V <sub>n</sub> (V) V <sub>n</sub> (V)	conf. pack.
2301051	BCH 1x51	1P	1,5	—	—	50A	690V	6-72
2304151	SBCH 1x51	1P	1,5	X	—	50A	690V	6-72
2305051	BCH/P 1x51 <sup>(1)</sup>	1P	1,5	—	X	50A	690V	6-72
2301151	BCH 1x51N	1P+N	3	—	—	50A	690V	3-36
2302051	BCH 2x51	2P	3	—	—	50A	690V	3-36
2303051	BCH 3x51	3P	4,5	—	—	50A	690V	2-24
2304351	SBCH 3x51	3P	4,5	X	—	50A	690V	2-24
2305351	BCH/P 3x51 <sup>(1)</sup>	3P	4,5	—	X	50A	690V	2-24
2303151	BCH 3x51N	3P+N	6	—	—	50A	690V	1-12

Omologazione   
(1) Per fusibili CH/P14 con percussore

approval  
(1) Fuses CH/P14 with striker must be used

### BCH 58 - PORTAFUSIBILI SEZIONABILI (AC-20B) PER FUSIBILI CILINDRICI 22X58 BCH 58 - MODULAR FUSEHOLDERS (AC-20B) FOR 22X58 CYLINDRICAL FUSES

codice IW IW code	tipo type	n. poli poles	n. moduli 17,5 mm no. 17,5 mm modules	indicatore luminoso indicator light	micro microswitch	I <sub>n</sub> (A) I <sub>n</sub> (A)	V <sub>n</sub> (V) V <sub>n</sub> (V)	conf. pack.
2301058	BCH 1x58	1P	2	—	—	125A	690V	6-48
2304158	SBCH 1x58	1P	2	X	—	125A	690V	6-48
2305058	BCH/P 1x58 <sup>(1)</sup>	1P	2	—	X	125A	690V	6-48
2301158	BCH 1x58N	1P+N	4	—	—	125A	690V	3-24
2302058	BCH 2x58	2P	4	—	—	125A	690V	3-24
2303058	BCH 3x58	3P	6	—	—	125A	690V	2-16
2304358	SBCH 3x58	3P	6	X	—	125A	690V	2-16
2305358	BCH/P 3x58 <sup>(1)</sup>	3P	6	—	X	125A	690V	2-16
2303158	BCH 3x58N	3P+N	8	—	—	125A	690V	1-8

Omologazione   
(1) Per fusibili CH/P22 con percussore

approval  
(1) Fuses CH/P22 with striker must be used